

3COM-2741

UNITED STATES PATENT APPLICATION

FOR

PERFORMANCE INDICATOR FOR WIRELESS DIGITAL SIGNAL RECEPTION

Inventor:

PAUL FULTON

Prepared by:

WAGNER, MURABITO & HAO LLP

Two North Market

Third Floor

San Jose, California 95113

005101#64955500

PERFORMANCE INDICATOR FOR WIRELESS DIGITAL SIGNAL RECEPTION

TECHNICAL FIELD

The present claimed invention relates to the field of wireless communication
5 of digital data. Specifically, the present claimed invention relates to an indicator
that displays the reception performance of a digital signal for a wireless receiver.

BACKGROUND ART

Wireless communication is growing increasingly popular in all areas of
10 business and personal use. Technology areas that use wireless communication
include telecommunication, networks, Internet, and audio and video media.
Furthermore, much of the wireless data is presented in a digital format, which in
itself provides opportunities for improved processing. Resultantly, a constant need
exists to improve performance and fidelity of wireless communication systems.

15

Referring now to prior art Figure 1A, an illustration of multipath signal
propagation occurring in wireless communication is shown. More specifically, the
wireless communication occurs between two devices, e.g., a station 104 and a
portable device 102. Station 104 can be a base station for a cell phone, while
20 portable device 102 can be a mobile phone. Alternatively, station 104 can be an
audio/video broadcaster that transmits digitally encoded data that is received by a
television or a personal computer (PC) 102. The wireless communication system
and the devices can span a wide variety of media and applications.

INS 117

The problem of multipath interference in wireless communication is illustrated in prior art Figure 1A. A transmitted signal can follow multiple paths, or multipaths, to arrive at a receiver. For example, one signal path, e.g., main 106a, transmits directly to a receiver 102 without any interference. However, due to
5 natural and man-made obstructions, such as building 108, hill 110, and surface 112, almost duplicate versions of the original signal arrive at receiver 102 with slight variations in phase, amplitude, and angle of arrival at receiver 102. These multipath can cause interference and destructive interference between each other.

INS 127

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000

Referring now to prior art Figure 1B, a graph of signal performance with a specific interference referred to as fading is shown. Graph 100b has a spatial X-Y plane defined by axis X 124 and axis Y 126. The vertical axis represent amplitude 122 of a signal that can be received at different spatial X, Y locations. Plane 134 defines an approximate amplitude of a transmitted signal in relation to the spatial
15 location of a receiver, e.g., an antennae. Areas of plane 134 having an attenuated amplitude 136 is indicative of Rayleigh fading of the signal. Rayleigh fading is characterized by spatially repeating deep fading areas that severely effects wireless communication performance. If an antennae is positioned in one or more of these pockets 136 of Rayleigh fading, then reception quality of a wireless signal
20 can be significantly compromised. Multipath fading occurs when a receiver receives not only the direct signal from a transmitter, but also reflected signals that differ from the direct signal in amplitude, phase, and/or angle of arrival, e.g., multipath B 106b, multipath C 106c, and multipath D 106d of prior art Figure 1A.

Multipath fading is directly related to the environment in which the receiver is working. For example, the Institute of Electrical and Electronic Engineers (IEEE) standard 802.11 for wireless local area network (LAN) employs frequencies of 2.4 gigahertz (GHz). However, at this frequency moving human bodies affect the
5 multipath fading, sometimes to a greater extent than building construction. In fact, much research has shown that at 2.4 GHz, Rayleigh type fading occurs. Consequently, a need arises to overcome the Rayleigh fading that degrades wireless communication performance. A more specific need arises to solve multipath fading in applications, such as wireless LANs, that have a high sensitivity
10 to this performance degradation.

One method of avoiding these deep fading areas, is to use antenna diversity at a receiver. Antenna diversity simply uses two antennas that are spatially or polarity separated such that only one antenna would be in a deep fade area. The
15 problem with this solution is that the user's receiver in typical IEEE 802.11 application is usually implemented on a peripheral component (PC) card, which does not allow for a large enough antenna separation to substantially reduce the Rayleigh fading. Additionally, even if antennas with polarity diversity are used, they do not always provide adequate escape from Rayleigh fading. Consequently, a
20 need arises for a method to avoid Rayleigh type fading when antennae diversity is ineffective or unsuitable.

Conventional methods have provided performance indicators, such as signal strength or SNR ratios, to indicate the reception quality of the radio.
25 However, these methods and indicators are primarily for analog systems, and are

not optimum for digital systems. Thus, their interpretation of good reception or a good signal is not necessarily applicable to that for a digital signal.

Referring now to prior art Figure 1C, a graph of exemplary data and noise signals is shown. Graph 100c has an abscissa of time 124 and an ordinate of amplitude 120. Three cases of data/noise signal combinations are shown for illustrative purposes. Case 1 121 shows just a data signal 121d with no indication of noise amplitude. If a conventional performance indicator only provides the strength of a data signal, as shown in Case 1 121, then it can be misleading. While data signal may have acceptable amplitude, if a noise signal has sufficient amplitude, it may significantly corrupt the data signal. In contrast, Case 2 122 shows a data signal amplitude 122d and a noise signal amplitude 122n. By using the conventional signal-to-noise (SNR) ratio, a relative strength of the data signal with respect to the noise signal can be obtained. However, as shown by case 3 123, signals with substantially different absolute amplitudes can appear to be equal (e.g., case 2 122 and case 3 123) based only on their ratio of signal to noise. Based on the limitations of conventional indicators, they are unsuitable, in general, to evaluate the accuracy and reception quality of a digital signal. Consequently, a need arises for a performance indicator that is more applicable to digital data.

20

Furthermore, the solution that eliminates or alleviates Rayleigh type fading and provides indication of good digital signal quality should be intuitive and simple to use, so as to promote implementation and compatibility. That is, the solution should not require the user to have apriori radio, computer, or any other technical knowledge to operate or understand it. In addition, the solution to Rayleigh fading

and the indicator digital signal performance should not require significant interaction of the hosting device such that system performance is hampered.

In summary, a need exists to improve performance and fidelity of wireless communication. A need also arises to overcome the Rayleigh fading that degrades wireless communication performance. A more specific need arises to solve multipath fading in applications, such as wireless LANs, that have a high sensitivity to this performance degradation. Another need arises for a method to avoid Rayleigh type fading when antennae diversity is ineffective or unsuitable. Based on the limitations of conventional indicators, a need arises for a performance indicator that is more applicable to digital data. Furthermore, the solution that eliminates or alleviates Rayleigh type fading and provides indication of good digital signal quality should be intuitive and simple so as to promote implementation and compatibility. That is, the solution should not require the user to have apriori radio, computer, or any other technical knowledge to operate or understand it. In addition, the solution to Rayleigh fading and the indicator of digital signal performance should not excessively burden the hosting device such that system performance is hampered.

SUMMARY OF THE INVENTION

The present invention provides a performance indicator for wireless digital signal reception, thereby improving performance and fidelity of wireless communication systems. The present invention also provides a method of overcoming the Rayleigh fading that otherwise degrades wireless communication performance. The present invention is effective for sensitive applications such as wireless LANs, or in cases where antennae diversity alone is ineffective or unsuitable. The present invention provides a performance indicator that is more applicable to digital data, and is intuitive and simple to use, thereby promoting implementation and compatibility with existing systems. That is, the solution does not require the user to have apriori radio, computer, or any other technical knowledge to operate or understand it. In addition, the present invention does not require interaction of the hosting device. In this manner, the indicator does not hamper system performance.

In one embodiment, the present invention recites a method for indicating the reception quality of a wireless digital signal in an electronic device. The method includes a series of steps, starting with a first step of receiving the wireless digital signal at the electronic device. In the next step, the wireless signal is demodulated. Then, an error rate associated with the digital data portion of the wireless signal is determined. The error rate of the packet of digital data can be determined by any rate, such as a cyclic redundancy code (CRC) algorithm, or a forward error correction (FEC) algorithm. In the next step, a quality level of reception of the wireless signal is indicated. Specifically, the quality level of reception is directly

proportional to the error rate of the signal. Thus, for example, the present embodiment provides an LED with a low flashing rate for a receiver with poor reception, e.g., a high error rate, of a wireless digital signal. Alternatively, the present embodiment provides an LED with a high flashing rate for a receiver with good reception, e.g., a low error rate, of a wireless digital signal. The reception quality indicator can provide valuable information to a user, or provide feedback to a controllable reception variable, thereby promoting accurate placement of an antennae and/or transceiver for the best quality of reception.

10 In another embodiment, the present invention recites a communication device including an antennae, a transceiver, an indicator, a processor, and a computer readable memory, all coupled to each other. The memory portion of the communication device contains data and program instructions that, when executed via the processor, implement the aforementioned method for providing a reception quality indicator for a wireless digital signal.

These and other objects and advantages of the present invention will become apparent to those of ordinary skill in the art after having read the following detailed description of the preferred embodiments which are illustrated in the various drawing figures.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and form part of this specification, illustrate embodiments of the invention and, together with the
5 description, serve to explain the principles of the invention. The drawings referred to in this description should be understood as not being drawn to scale except as specifically noted.

PRIOR ART FIGURE 1A is an illustration of multipath signal propagation for a
10 wireless communication system.

PRIOR ART FIGURE 1B is a graph of signal performance with Rayleigh
fading effects.

15 PRIOR ART FIGURE 1C is a graph of conventional exemplary data and noise signals.

FIGURE 2A is a hardware block diagram of a wireless device for indicating
reception quality of a digital signal, in accordance with one embodiment of the
20 present invention.

FIGURE 2B is a block diagram of the functions performed, and the data transfer provided, by a wireless device indicating reception quality of a digital signal, in accordance with one embodiment of the present invention.

FIGURE 3A is a flow chart of the steps performed to indicate reception quality of digital signal on a wireless device, in accordance with one embodiment of the present invention.

5

FIGURE 3B is a flow chart of the steps performed to indicate a maximum reception quality of digital signal on a wireless device, in accordance with one embodiment of the present invention.

10 FIGURE 3C is a flow chart of the steps performed for feedback control to a reception portion of a wireless device with respect to the reception quality, in accordance with one embodiment of the present invention.

BEST MODE FOR CARRYING OUT THE INVENTION

Reference will now be made in detail to the preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings. While the invention will be described in conjunction with the preferred embodiments, it
5 will be understood that they are not intended to limit the invention to these embodiments. On the contrary, the invention is intended to cover alternatives, modifications and equivalents, which may be included within the spirit and scope of the invention as defined by the appended claims. Furthermore, in the following detailed description of the present invention, numerous specific details are set forth
10 in order to provide a thorough understanding of the present invention. However, it will be obvious to one of ordinary skill in the art that the present invention may be practiced without these specific details. In other instances, well-known methods, procedures, components, and circuits have not been described in detail, so as not to unnecessarily obscure aspects of the present invention.

15
Some portions of the detailed descriptions which follow, e.g., the processes, are presented in terms of procedures, logic blocks, processing, and other symbolic representations of operations on data bits within a computer or digital system memory or on signals within a communication device. These descriptions and
20 representations are the means used by those skilled in the digital communication arts to most effectively convey the substance of their work to others skilled in the art. A procedure, logic block, process, etc., is herein, and generally, conceived to be a self-consistent sequence of steps or instructions leading to a desired result. The steps are those requiring physical manipulations of physical quantities. Usually,
25 though not necessarily, these physical manipulations take the form of electrical or

magnetic signals capable of being stored, transferred, combined, compared, and otherwise manipulated in a communication device or a processor. For reasons of convenience, and with reference to common usage, these signals are referred to as bits, values, elements, symbols, characters, terms, numbers, or the like with
5 reference to the present invention.

It should be borne in mind, however, that all of these terms are to be interpreted as referencing physical manipulations and quantities and are merely convenient labels to be interpreted further in view of terms commonly used in the
10 art. Unless specifically stated otherwise as apparent from the following discussions, it is understood that throughout discussions of the present invention, terms such as "receiving," "demodulating," "determining," "indicating," "updating," "recording," "identifying," "providing," "adjusting," or the like, refer to the action and processes of a communication device or a similar electronic computing device, that manipulates
15 and transforms data. The data is represented as physical (electronic) quantities within the communication device components, and is transformed into other data similarly represented as physical quantities within the communication device components, or other such information storage, transmission or display devices.

20 Referring now to Figure 2A, a hardware block diagram of a wireless device for indicating reception quality of a digital signal is shown, in accordance with one aspect of the present invention. In the present embodiment communication device 200a is a radio frequency (RF) peripheral component (PC) card, capable of being
25 200a is configurable to determine the reception performance of a wireless digital

signal, in the present embodiment. Electronic device 200a provides a reception quality indication output 207. This output can be utilized by a user or an electronic system to evaluate and improve the reception quality of the electronic device.

5 Communication device 200a can be a wide range of devices, including stand-alone or integrated devices, that are incorporated into a wide range of applications. For example, communication device 200a can be any type of PC card or integrated component that is used in a standalone PC, a network device, a server, a printer, etc. In brief, communication device 200a can be any electronic
10 device that receives a digital wireless signal. Furthermore, communication device 200a can be incorporated into a personal communication device such as a cell phone, a personal digital assistant (PDA) with wireless communication capabilities, or entertainment media such as a television, a satellite dish, etc. By incorporating an indicator 205, with the appropriate instructions in memory 206 executed via
15 processor 204, the present invention provides a more appropriate indicator of receiver performance for a wireless digital signal.

Communication device 200a includes a processor 204, memory 206, transceiver 208, indicator 205 and antennae 203. Antennae 203 is coupled to
20 transceiver 208. Transceiver 208 is coupled to processor 204, volatile memory 206, indicator 205, and non-volatile memory 208 via bus 202. Bus 202 provides data and control lines for the transmission of data and commands between the interconnected components. Memory 206 can include either volatile memory and/or non-volatile memory. Basic Input/Output system instructions can be stored
25 in non-volatile memory portion of memory 206 for operating communication device

200a. Similarly, software or firmware code for determining the reception performance of a wireless digital signal can be stored in volatile memory or in non-volatile memory, respectively, portions of memory 206. If code is stored on volatile memory portion of memory 206, then it must be loaded from either non-volatile memory, or from a data storage device, such as a system hard drive or floppy drive, not shown in the present embodiment. The instructions stored as firmware or software code are executed using the processor in harmony with other components shown in Figure 2A. While the present embodiment uses a transceiver 204 to receive signals from antennae 203, the present invention is well-suited to using a receiver to receive the signals.

Indicator 205 of Figure 2A is a light emitting diode (LED) in the present embodiment that provides an indication of reception performance of a digital wireless signal. However, indicator 205 can be any combination of audio or visual elements that convey a message corresponding to the reception performance of a digital wireless signal by the communication device, e.g., specifically at the antennae and transceiver. Specific configurations of indicator 205 and correlation to reception performance of wireless digital signals is described hereinafter in the flowchart figures for the process.

20

Referring now to Figure 2B, a block diagram of the functions performed, and the data transfer provided, by a wireless device indicating reception quality of a digital signal is shown, in accordance with one embodiment of the present invention. The function blocks can be implemented using one or more of the components of wireless device such as 200a of Figure 2A. Block diagram 200b

begins with the input of a baseband signal 219 provided to demodulate block 220. Demodulate block 220 outputs a data signal 221 to decode block 224 which outputs a digital data 223, e.g. via an analog to digital (A to D) converter, and/or encryption decoder. Error calculation block 226 evaluates digital data signal 223 and provides an error rate 227, such as packet error rate (PER), associated with the data signal. Finally, feedback block 228 receives the PER data 227 and provides a reception quality 229 as output. This flow of data and functions provides an indication of reception quality such that the reception can be improved, thereby increasing productivity of wireless communication.

10

Referring now to Figure 3A, a flowchart embodiment of a process for indicating the reception quality of digital signal on a wireless device is shown, in accordance with one embodiment of the present invention. The steps of flowchart 3000a can be implemented in one embodiment by the various components of communication device 200a of Figure 2A. In particular, the queries and the logic of process 3000a can be implemented using a state machine or by using firmware/software, stored in memory 206, executed via processor 204 to control other components of communication device 200a. By implementing the flowchart 3000a embodiment of the present invention, the quality of digital signal on a wireless device, the overall quality, fidelity, and performance of the communication system is enhanced by indicating the digital wireless signal reception.

Process 3000a begins with step 3002. In step 3002 of the present embodiment, a wireless signal is received. Step 3002 is implemented, in one embodiment, by antennae 203 shown in Figure 2. Antennae 203 picks up the

wireless signal, e.g., a main signal and/or its multipath versions. Following step 3002, process 3000a proceeds to step 3004.

In step 3004 of the present embodiment, the wireless signal is demodulated.

5 Step 3004 is accomplished, in one embodiment, by transceiver 208 shown in Figure 2. A receiver can be utilized for step 3004 in lieu of a transceiver. Step 3004 can also include a substep, not shown in Figure 3A, of converting an analog signal received by antennae 203 to a digital signal (e.g., a "A to D" conversion) that is well-known in the art. Step 3004 essentially obtains the data signal from the
10 baseband signal and converts it to a digital format that is appropriate for subsequent digital signal processing (DSP). The demodulation step is well-known by those skilled in the art. The present invention is also well-suited to a signal that is multiplexed with other signals. For example, signal transmission such as time-division multiplexing (TDM), code division multiple access (CDMA), frequency
15 division multiplexing (FDM), and other forms of multiplexing are well-suited to implementation by the present invention. Following step 3004, process 3000a proceeds to step 3006.

In step 3006 of the present embodiment, an error rate is determined. Step
20 3006 is accomplished, in one embodiment, by a packet error rate (PER) calculation. However, the present invention is well-suited to using other error-checking methods or algorithms for determining the accuracy of the digital data received by the electronic device. The PER of the present embodiment can be determined by a wide variety of methods. For example, the PER can be

determined by methods such as the cyclic redundancy code (CRC) or a Forward error correction (FEC) algorithm.

5 The CRC method checks a parity bit to determine if a data packet of a received digital signal has an error or not. This method is a qualitative measurement capable only of a binary outcome, either the packet has no errors and therefore is acceptable, or it has at least one error, and is therefore unacceptable. In contrast, the FEC algorithm can determine the amount of correction required to a data packet. One example of a FEC algorithm is the Reed-
10 Solomon method. An FEC algorithm provides a quantitative indication of the amount of errors in a given data packet. Either of these two methods can provide error information to the following steps for evaluation. Following step 3006, process 3000a proceeds to step 3008.

15 In step 3008 of the present embodiment, a quality level of reception is determined. Step 3008 is accomplished, in one embodiment, using a software algorithm, implemented by electronic device 200a of Figure 2A. That is, step 3008 associates a quality level with a given error rate. Step 3008 can be implemented using software memory executed by a processor such as a look up table or an
20 algorithm. Alternatively, step 3008 can be implemented using hardware such as logic gates.

The present invention is well-suited to using any relationship between a quality level and an error rate. For example, a linear or nonlinear relationship can
25 be established between the error rates and the quality levels. The variables

associated with the error rate can be significant. For example, the 'number of errors' in a data packet can be an indication of reception quality. Also, the 'frequency' of packets that have the number of errors can be an indication of the reception quality.

5

In one embodiment of step 3008, a non-linear relationship is used for a receiver using a non-error correcting algorithm for decoding the digital signal. This is because as the error rate increases even slightly from a zero-error level, the entire data packet typically becomes useless. That is, in a non-error-correcting algorithm, any error in the reception of a data packet implicitly requires the retransmission of the data, a resource-intensive process. Consequently, in this scenario, the frequency of data packets having any quantity of errors of all becomes very critical. Evaluating this embodiment with the scenarios of Table 1, shown hereinafter, results in the following Pareto sequence of desirable reception:

10 scenario 1 provides the best reception because it has no errors in any data packets; scenario 3 provides the second best reception because it has some error in only one of the data packets, scenario 2 provides the third best reception because it has some error in two of the data packets; scenario 4 and 5 equivalently provide the worst reception because, regardless of the amount of error rate, all data

15 packets have at least some errors, and are therefore unacceptable.

20

In another embodiment of step 3008, an error-correcting algorithm is used in the electronic device receiving and decoding the digital signal. In this embodiment, errors can be identified and compensated for in the electronic device receiving the

25 digital signal. However, the quantity of errors as well as the frequency of the data

packets having the errors now becomes significant because they will consume system resources to correct the errors. Thus, this embodiment can utilize a linear relationship because errors in a packet can be corrected, with each additional error consuming additional system resources to correct. At some point, a sufficient

5 quantity of errors may dictate the retransmission of the data packet, thereby justifying a non-linear relationship between the quantity of errors and the quality level of the reception. However, many different strategies can be accommodated by the present invention. Evaluating this embodiment with the scenarios of Table 1, shown hereinafter, results in the following Pareto sequence of desirable
10 reception: scenario 1 is best because it has no errors in any data packets; scenario 2 is second because it has only 5% PER in each of two data packets, scenario 3 is third because it has 55% PER in one data packet; scenario 4 is fourth because it has 55%, 5% and 5% PER for the three respective data packets; scenario 5 is last because it has high error rates in all packets. Thus, the present embodiment is
15 sensitive to the cumulative errors in data packets. In lieu of simple strength indications of a signal, more appropriate for an analog signal, the present invention appropriately indicates the quality of the digital data. Following step 3008, process 3000a proceeds to step 3010.

20 Table 1 - Error Rate Scenarios

Scenario	ERROR Rate in Packets (PER)			Reception QUALITY	
	Data Packet 1	Data Packet 2	Data Packet 3	NON-Error Correcting	Error Correcting
1. No Error - All Packets	0	0	0	Best	Best
2. Low Error - Some Packets	5%	0	5%	Medium	Good
3. Hi Error- Some Packets	55%	0	0	Medium	Medium
4. Low Error - All Packets	55%	5%	5%	Worst	Medium
5. Hi Error- All Packets	80%	75%	85%	Worst	Worst

In step 3010 of the present embodiment, the quality level of reception is indicated. Step 3010 is accomplished, in one embodiment, by providing a signal to a light emitting diode (LED) of indicator 205 of Figure 2A. However, the quality level of reception can be indicated by any combination of audio, video, or other type of output. Furthermore the variation in the output can span a wide variety of embodiments. For example, the 'indication' of quality level can be tied to a variable quantity of illuminated LEDs. That is, more LEDs illuminate for a stronger wireless digital signal reception quality and less LEDs illuminate for a weaker signal quality. Alternatively, the rate at which an LED flashes can vary depending on the reception quality of the signal. For example, an LED can flash at a faster rate for a stronger reception quality, and flash at a slower rate for a weaker reception quality.

The following table, Table 2, provides a specific embodiment that implements step 3010. Table 2 provides incremental ranges of Packet Error Rate (PER) that a wireless receiver may yield for a digital signal it has received. For example, a first category is for a PER in the range of 0-10%, a second category is for a PER between 10-30%, etc. The rows across the top of the table represent different possible system data rates. Thus, the first scenario is for an 11 mega bits per second (Mbps) data rate, the second scenario is for a 5.5 Mbps data rate, and the final scenario is for a 2 Mbps data rate. However, this embodiment can be scaled for any data rate. The boxes below the processor rates, and across from the PER categories indicate the 'duty cycle' of an LED used to indicate the reception quality for a wireless digital signal. For example, if a wireless digital signal is

received at 11 Mbps data rate at a PER of 5%, then the indicator LED would have a duty cycle of 20 ms 'on' followed by 5 ms 'off' (e.g., a fast flashing rate) to indicate the quality level of reception. However, if the PER for the same processor rose to 75%, then the indicator LED would have a duty cycle of 30 ms 'on' followed by a

5 200 ms 'off' (e.g., a slow flashing rate) to indicate the quality level of reception.

Using the formula of the present embodiment, the LED would flash more frequently as the maximum reception quality was attained for the wireless digital signal.

Similarly, the present embodiment would result in the LED flashing less frequently for a poor reception quality. Following step 3010, process 3000a ends.

10

Table 2 Indication Rate

Packet Error Rate (PER) [averaged over 500 ms]	11 Mbps		5.5 Mbps		2 Mbps	
	On	Off	On	Off	On	Off
00% < PER < 10 %	20 ms	5 ms	40 ms	10 ms	40 ms	10 ms
10% < PER < 30 %	20 ms	20 ms	40 ms	30 ms	40 ms	30 ms
30% < PER < 50 %	30 ms	30 ms	40 ms	60 ms	40 ms	60 ms
50% < PER < 70 %	30 ms	50 ms	40 ms	100 ms	40 ms	100 ms
70% < PER < 90 %	30 ms	70 ms	40 ms	140 ms	40 ms	140 ms
90% < PER < 100 %	30 ms	200 ms	40 ms	400 ms	40 ms	400 ms

Flowchart 3000a can be repeated indefinitely, thus providing a real-time indication of the quality level of reception of a communication device at all times.

15 Alternatively, once a position has been obtained, the indicator output may no longer be necessary, and therefore may be discontinued.

Referring now to Figure 3B, a flowchart embodiment of a process to indicate maximum reception quality of digital signal on a wireless communication device is

20 shown, in accordance with one embodiment of the present invention. The steps of flowchart 3000b can be implemented in one embodiment by the various

components of communication device 200a of Figure 2A. In particular, the queries and the logic of flowchart 3000b can be implemented using a state machine or by using firmware/software, stored in memory 206, and executed via processor 204 to control other components of communication device 200a. By implementing
5 flowchart 3000b embodiment of the present invention, a 'maximum' reception quality for a digital wireless signal can be achieved quickly and accurately.

Process 3000b begins with step 3022. In step 3022 of the present embodiment, a history of quality levels is recorded. Step 3022 is implemented, in
10 one embodiment, by iterating process 3000a using components of Figure 2A over a period of time and recording the results in memory 206 of Figure 2A. In one embodiment, an input of a time value 3022a, can provide a time limit over which the quality level of a signal is evaluated. For example, a time input of 15 seconds can be chosen in one embodiment, although the present invention is well-suited to
15 using any quantity of time. During the timespan, an antennae's position can be rotated, translated, or moved in a wide variety of ways during the time period. By automatically detecting the maximum possible reception quality via the electronic device, a user is alleviated from a potentially intensive operation of both moving the antennae and trying to identify the position yielding the maximum reception quality.
20 Following step 3022, process 3000b proceeds to step 3024.

In step 3024 of the present embodiment, a maximum quality level of reception is identified. Step 3024 is accomplished, in one embodiment, after expiration of a time limit, e.g., set by time input 3020a. Specifically, the processor
25 can use a comparison algorithm to choose a baseline quality level and compare it

to subsequent quality levels, repeatedly reestablishing the baseline with any quality level that exceeds it. In other words, steps 3022 and 3024 may only be able to identify the maximum reception quality level after all other quality levels have been identified as less than the maximum. Following step 3024, process 3000b
5 proceeds to step 3026.

In step 3026 of the present embodiment, new quality levels are received. Step 3026 can be performed after the expiration of the time limit used to detect the maximum reception quality level. In step 3026, the antennae can be repositioned
10 to try and duplicate the position that created the maximum quality reception level in step 3022-3024, with the electronic device providing an indication when the maximum quality reception level is matched. Following step 3026, process 3000b proceeds to step 3028.

15 In step 3028 of the present embodiment, an inquiry determines whether the new quality level is equal to, or greater than, the maximum value, e.g., the maximum level output 3022a from step 3024. If the new quality level is equal to or greater than the maximum value, then the flowchart 3000b proceeds to step 3030. However, if the new quality level does not exceed the maximum value, then
20 process 3000b returns to step 3026. Step 3028 provides the logic for comparing and identifying the point at which the new quality level meet or exceeds the previously identified maximum quality level. Step 3028 is one of several possible embodiments for identifying the maximum quality level of reception for the present invention.

Step 3030 arises if the new quality level is equal to or greater than the maximum value, per step 3028. In step 3030 of the present embodiment, an indication is provided. Because step 3030 arises only when a new quality level is equal to or greater than the maximum quality level, the indication provided by step 3030 necessarily identifies the antennae orientation at which the maximum quality level is achieved. Foreseeable variations, e.g., hysteresis, in the quality level can occur between the searching phase of steps 3022-3024 and the positioning phase of steps 3026-3030. These variations may be accounted for using techniques known by those skilled in the art. Following step 3030, process 3000b ends.

Referring now to Figure 3C, a flowchart embodiment of a process for providing feedback control to a reception portion of a wireless device with respect to the reception quality is shown, in accordance with one embodiment of the present invention. The steps of flowchart 3000c can be implemented in one embodiment by the various components of communication device 200a of Figure 2A. In particular, the queries and the logic of flowchart 3000c can be implemented using a state machine or by using firmware/software, stored in memory 206, executed via processor 204 to control other components of communication device 200a. By implementing the flowchart 3000c embodiment of the process for indicating the reception quality of digital signal on a wireless device, the overall quality, fidelity, and performance of the communication system is enhanced.

Process 3000c begins with step 3042. In step 3042 of the present embodiment, an error rate is received. Step 3042 is implemented, in one

embodiment, similar to the implementation of step 3006 of flowchart 3000a. In lieu of the error rate, the quality level of reception can be received. Following step 3042, process 3000c proceeds to step 3044.

5 In step 3044 of the present embodiment, feedback to a controllable variable that affects reception is provided. Step 3044 takes the error rate or the quality level provided by step 3042 and converts it to an electronic signal capable of manipulating other electronic components associated with the reception quality of a wireless digital signal. In other words, the error rate or quality level can be
10 translated into a signal that affects the position of the antennae, the amplification of the signal, or other similar control variables that affect the reception of the signal. Step 3044 is accomplished, in one embodiment, using control system logic that is well known by those skilled in the art. Following step 3044, process 3000c proceeds to step 3046.

15 In step 3046 of the present embodiment, the controllable variable is adjusted to improve reception. Step 3046 receives the electronic signal from step 3044 and implements it to manipulate other electronic components antenna phase, antenna physical position or software associated with the reception quality of a wireless
20 digital signal. In this manner, the present invention provides a reception system that automatically provides the highest reception quality level possible for the received digital signal. Following step 3046, process 3000c ends.

 While process embodiments in flowcharts 3000a, 3000b, and 3000c use a
25 specific sequence and quantity of steps, the present invention is suitable to

alternative embodiments. For example, not all the steps provided for these processes are required for the present invention. Furthermore, additional steps can be added to the steps presented in the present embodiment. Likewise, the sequence of the steps can be modified depending upon the application. While
5 these processes is shown as a single serial process, it can also be implemented as a continuous or parallel process.

Many of the instructions for the steps, and the data input and output from the steps of process embodiments in flowcharts 3000a, 3000b, and 3000c is
10 implemented utilizing memory 206 and utilizing processor 204, as shown in Figure 2. Memory storage 206 of the present embodiment can include both permanent memory, such as read only memory (ROM), and temporary memory such as random access memory (RAM). ROM memory can be utilized to store data for permanent functions of the dedicated service module, while RAM memory can be
15 utilized to store data related to the on-site media service data. Memory 206 can include other types of memory storage, capable of containing data, such as a hard drive, a CD ROM, or flash memory. Furthermore, processor 204 can either be a dedicated controller, an existing system processor, or it can be a dedicated digital signal processing (DSP) processor. Alternatively, the instructions can be
20 implemented using some form of a state machine.

In view of the embodiments presented herein, the present invention provides a performance indicator for wireless digital signal reception, thereby improving performance and fidelity of wireless communication systems. The
25 present invention also provides a method of overcoming the Rayleigh fading that

otherwise degrades wireless communication performance. The present invention is effective for sensitive applications such as wireless LANs, or in cases where antennae diversity alone is ineffective or unsuitable. The present invention provides a performance indicator that is more applicable to digital data, and is
5 intuitive and simple to use, thereby promoting implementation and compatibility with existing systems. That is, the solution does not require the user to have apriori radio, computer, or any other technical knowledge to operate or understand it. In addition, the present invention does not require interaction of the hosting device. In this manner, the indicator does not hamper system performance.

10

The foregoing descriptions of specific embodiments of the present invention have been presented for purposes of illustration and description. They are not intended to be exhaustive or to limit the invention to the precise forms disclosed, and obviously many modifications and variations are possible in light of the above
15 teaching. The embodiments were chosen and described in order to best explain the principles of the invention and its practical application, to thereby enable others skilled in the art to best utilize the invention and various embodiments with various modifications as are suited to the particular use contemplated. It is intended that the scope of the invention be defined by the Claims appended hereto and their
20 equivalents.